

Metric/Decimal

Metric/Decimal Equivalents

	Inches	Millimeters
	1/64	.015625 0.3969
1/32	.031250	0.7938
	.039370	— 1
1/16	3/64	.046875 1.1906
	.062500	1.5875
	5/64	.078125 1.9844
	.078740	— 2
3/32	.093750	2.3812
	7/64	.109375 2.7781
	.118110	— 3
1/8	.125000	3.1750
	9/64	.140625 3.5719
5/32	.156250	3.9688
	.157480	— 4
3/16	11/64	.171875 4.3656
	.187500	4.7625
	.196850	— 5
	13/64	.203125 5.1594
7/32	.218750	5.5562
	15/64	.234375 5.9531
	.236220	— 6
1/4	.250000	6.3500
	17/64	.265625 6.7469
	.275591	— 7
9/32	.281250	7.1438
	19/64	.296875 7.5406
5/16	.312500	7.9375
	.314961	— 8
	21/64	.328125 8.3344
11/32	.343750	8.7312
	.354331	— 9
3/8	23/64	.359375 9.1281
	.375000	9.5250
	25/64	.390625 9.9219
	.393701	— 10
13/32	.406250	10.3188
	27/64	.421875 10.7156
	.433071	— 11
7/16	.437500	11.1125
	29/64	.453125 11.5094
	15/32	.468750 11.9062
	.472441	— 12
	31/64	.484375 12.3031
1/2	.500000	12.7000
	.511811	— 13

	Inches	Millimeters
	33/64	.515625 13.0969
17/32	.531250	13.4938
	35/64	.546875 13.8906
	.551181	— 14
9/16	.562500	14.2875
	37/64	.578125 14.6844
	.590551	— 15
19/32	.593750	15.0812
	39/64	.609375 15.4781
5/8	.625000	15.8750
	.629921	— 16
	41/64	.640625 16.2719
21/32	.656250	16.6688
	.669291	— 17
	43/64	.671875 17.0656
11/16	.687500	17.4625
	45/64	.703125 17.8594
	.708661	— 18
23/32	.718750	18.2562
	47/64	.734375 18.6531
	.748031	— 19
3/4	.750000	19.0500
	49/64	.765625 19.4469
25/32	.781250	19.8438
	.787402	— 20
	51/64	.796875 20.2406
13/16	.812500	20.6375
	.826775	— 21
	53/64	.828125 21.0344
27/32	.843750	21.4312
	55/64	.859375 21.8281
	.866142	— 22
7/8	.875000	22.2250
	57/64	.890625 22.6219
	.905512	— 23
29/32	.906250	23.0188
	59/64	.921875 23.4156
15/16	.937500	23.8125
	.944882	— 24
	61/64	.953125 24.2094
31/32	.968750	24.6062
	.984252	— 25
	63/64	.984375 25.0031
1	1.00000	25.4000

Decimal Equivalents of Millimeters

mm	Inches	mm	Inches								
25	0.98425	38	1.49606	51	2.00787	64	2.51968	77	3.03149	90	3.54330
26	1.02362	39	1.53543	52	2.04724	65	2.55905	78	3.07086	91	3.58267
27	1.06299	40	1.57480	53	2.08661	66	2.59842	79	3.11023	92	3.62204
28	1.10236	41	1.61417	54	2.12598	67	2.63779	80	3.14960	93	3.66141
29	1.14173	42	1.65354	55	2.16535	68	2.67716	81	3.18897	94	3.70078
30	1.18110	43	1.69291	56	2.20472	69	2.71653	82	3.22834	95	3.74015
31	1.22047	44	1.73228	57	2.24409	70	2.75590	83	3.26771	96	3.77952
32	1.25984	45	1.77165	58	2.28346	71	2.79527	84	3.30708	97	3.81889
33	1.29921	46	1.81102	59	2.32283	72	2.83464	85	3.34645	98	3.85826
34	1.33858	47	1.85039	60	2.36220	73	2.87401	86	3.38582	99	3.89763
35	1.37795	48	1.88976	61	2.40157	74	2.91338	87	3.42519	100	3.93700
36	1.41732	49	1.92913	62	2.44094	75	2.95275	88	3.46456		
37	1.45669	50	1.96850	63	2.48031	76	2.99212	89	3.50393		

1 Inch = 25.400 mm



Temperature Conversions

°C – °F 0 to 40		
C	C or F	F
-17.80	0	32.0
-17.20	1	33.8
-16.70	2	35.6
-16.10	3	37.4
-15.60	4	39.2
-15.00	5	41.0
-14.40	6	42.8
-13.90	7	44.6
-13.30	8	46.4
-12.80	9	48.2
-12.20	10	50.0
-11.70	11	51.8
-11.10	12	53.6
-10.60	13	55.4
-10.00	14	57.2
-9.44	15	59.0
-8.89	16	60.8
-8.33	17	62.6
-7.78	18	64.4
-7.22	19	66.2
-6.67	20	68.0
-6.11	21	69.8
-5.56	22	71.6
-5.00	23	73.4
-4.44	24	75.2
-3.89	25	77.0
-3.33	26	78.8
-2.78	27	80.6
-2.22	28	82.4
-1.67	29	84.2
-1.11	30	86.0
-0.56	31	87.8
0.00	32	89.6
0.56	33	91.4
1.11	34	93.2
1.67	35	95.0
2.22	36	96.8
2.78	37	98.6
3.33	38	100.4
3.89	39	102.2
4.44	40	104.0

°C – °F 41 to 80		
C	C or F	F
5.00	41	105.8
5.56	42	107.6
6.11	43	109.4
6.67	44	111.2
7.22	45	113.0
7.78	46	114.8
8.33	47	116.6
8.89	48	118.4
9.44	49	120.2
10.00	50	122.0
10.60	51	123.8
11.10	52	125.6
11.70	53	127.4
12.20	54	129.2
12.80	55	131.0
13.30	56	132.8
13.90	57	134.6
14.40	58	136.4
15.00	59	138.2
15.60	60	140.0
16.10	61	141.8
16.70	62	143.6
17.20	63	145.4
17.80	64	147.2
18.30	65	149.0
18.90	66	150.8
19.40	67	152.6
20.00	68	154.4
20.60	69	156.2
21.10	70	158.0
21.70	71	159.8
22.20	72	161.6
22.80	73	163.4
23.30	74	165.2
23.90	75	167.0
24.40	76	168.8
25.00	77	170.6
25.60	78	172.4
26.10	79	174.2
26.70	80	176.0

°C – °F 81 to 250		
C	C or F	F
27.2	81	177.8
27.8	82	179.6
28.3	83	181.4
28.9	84	183.2
29.4	85	185.0
30.0	86	186.8
30.6	87	188.6
31.1	88	190.4
31.7	89	192.2
32.2	90	194.0
32.8	91	195.8
33.3	92	197.6
33.9	93	199.4
34.4	94	201.2
35.0	95	203.0
35.6	96	204.8
36.1	97	206.6
36.7	98	208.4
37.2	99	210.2
37.8	100	212.0
43.0	110	230.0
49.0	120	248.0
54.0	130	266.0
60.0	140	284.0
66.0	150	302.0
71.0	160	320.0
77.0	170	338.0
82.0	180	356.0
88.0	190	374.0
93.0	200	392.0
99.0	210	410.0
100.0	212	413.0
104.0	220	428.0
110.0	230	446.0
116.0	240	464.0
121.0	250	482.0

°C – °F 260 to 600		
C	C or F	F
127	260	500
132	270	518
138	280	536
143	290	554
149	300	572
154	310	590
160	320	608
166	330	626
171	340	644
177	350	662
182	360	680
188	370	698
193	380	716
199	390	734
204	400	752
210	410	770
216	420	788
221	430	806
227	440	824
232	450	842
238	460	860
243	470	878
249	480	896
254	490	914
260	500	932
266	510	950
271	520	968
277	530	986
282	540	1004
288	550	1022
293	560	1040
299	570	1058
304	580	1076
310	590	1094
316	600	1112

Temperature Conversion Formulas

NEED TO FIND	FORMULA
DEGREES (IN CELSIUS)	$.56 \times (\text{DEGREES F} - 32)$
DEGREES (IN FAHRENHEIT)	$(1.8 \times \text{DEGREES C}) + 32$

General Formulas

Drive System Mechanical Formulas

	NEED TO FIND:	FORMULA:
Mechanical	CIRCUMFERENCE OF A CIRCLE	3.1416 X DIAMETER
	DIAMETER OF A CIRCLE	$\frac{\text{CIRCUMFERENCE}}{(3.1416)}$
	VELOCITY IN FEET PER MINUTE	FPM = .262 X DIAMETER X RPM
	RPM REVOLUTIONS PER MINUTE	$\frac{\text{FEET PER MINUTE}}{(.262 \times \text{DIAMETER})}$
	TORQUE IN/LBS	$\frac{\text{HP} \times 63,025}{\text{RPM}}$
	TORQUE IN/LBS	FORCE (LBS) X RADIUS (IN)
	HORSEPOWER	$\frac{\text{TORQUE (IN.LBS)} \times \text{RPM}}{63,025}$
	HORSEPOWER	$\frac{\text{FORCE} \times \text{FPM}}{33,000}$
	BELT LENGTH	$[1.57 \times (\text{DIA} + \text{DIA})] + (2 \times \text{CENTER DIST})$
	MOTOR RPM SYNCHRONOUS	$\frac{120 \times 60 (\text{HZ})}{\text{NUMBER OF MOTOR POLES}}$
	PUMP MOTOR HP	$\frac{\text{GPM} \times \text{HEAD IN FEET} \times \text{SPEC GRAVITY}}{3960 \times \text{EFFICIENCY OF PUMP}}$
	FAN MOTOR HP	$\frac{\text{CFM} \times \text{PRESSURE (LB/SQ FT)}}{33000 \times \text{EFFICIENCY}}$

Formulas and Constants

1 hp = 33,000 / Foot-pounds of work per minute.

1 hp = .746 K.W. = K.W. ÷ 1.341.

1 hp = 2,547 B.T.U. per hour.

1 B.T.U. = Heat required to raise 1 lb. water 1 °F.

1 B.T.U. = 777.6 / Foot-pounds work.

1 Kilowatt Hour = 3,415 B.T.U.

Heat Value of Carbon = 14,600 B.T.U. per pound.

Latent Heat of Fusion of Ice = 143.15 B.T.U per pound.

Latent Heat of Evaporation of Water at 212 °F.

= 970.4 B.T.U. per pound.

Total Heat of Saturated Steam at Atmospheric Pressure

= 1,150.4 B.T.U. per pound.

1 Ton of Refrigeration = 288,000 B.T.U. per 24 hours.

g = Acceleration of Gravity

(commonly taken as 32.16 feet per second per second).

1 Radian = 57.296 degrees.

1 Meter = 100 cm. = 39.37 inches.

1 Kilometer = .62137 miles.

1 Gallon = 231 cubic inches.

1 Barrel = 42 gallons.

Atmospheric Pressure = 14.7 pounds per sq. in.

= 29.92 inches mercury at 32 °F.

1 Lb. Per Sq. In. Pressure = 2.3095 feet fresh water at 62 °F.

= 2.0355 inches mercury at 32 °F.

= 2.0416 inches mercury at 62 °F.

Water Pressure (pounds per sq. in.)

= .433 X height of water in feet (Fresh water at 62 °F).

Weight of 1 cu. ft. Fresh Water

= 62.355 lbs. at 62 °F. = 59.76 lbs. at 212 °F.

Weight of 1 cu. ft. Air at 14.7 lbs. per sq. in. Pressure

= .07608 lbs. at 62 °F = .08073 lbs. at 32 °F.



Horsepower

SPEED, in the science of bearing application and power transmission, is expressed in terms of the revolutions per minute (rpm) of a rotating object.

VELOCITY is speed in a designated direction and is usually expressed in terms of feet per minute (fpm).


FORCE is the element that produces a change in the velocity of an object. It is usually expressed in pounds.

WORK occurs when a force moves an object through a distance. It is usually expressed in foot-pounds or inch-pounds.

POWER is the rate of doing work. It is usually expressed in foot-pounds per minute (fppm).

HORSEPOWER is the unit of power. It is the power required to lift 33,000 pounds one foot in one minute.

Illustration of Horsepower



A **POUND-FOOT** is the moment created by a force of one pound applied to the end of a lever arm one foot long. Pound-feet indicate torque.

Example:

25 hp at 150 rpm = 10,504 Pound-Inches Torque
 25 hp at 1.50 rpm = 1,050,400 Pound-Inches Torque
 2.5 hp at 1.50 rpm = 105,040 Pound-Inches Torque

$$\text{HORSEPOWER (hp)} = \frac{\text{pounds (\#)} \times \text{feet}}{33,000 \times \text{no. minutes}}$$

$$\text{hp} = \frac{\text{Force (lb-in)} \times \text{fpm}}{33,000}$$

$$\text{hp} = \frac{\text{Torque (in lb-in)} \times \text{rpm}}{63,025}$$

$$\text{hp} = \frac{\text{Torque (in lb-ft)} \times \text{rpm}}{5,252}$$

Torque

TORQUE is the turning moment or twisting effort in a shaft or an object that tends to cause rotation. It is the measure of rotational force and is expressed in foot-pounds.

Torque = force in pounds x radius in inch or foot

$$\text{Torque (pound-inch)} = \frac{63,025 \times \text{hp}}{\text{rpm}}$$

$$\text{Torque (pound-foot)} = \frac{5,252 \times \text{hp}}{\text{rpm}}$$

$$\text{Horsepower} = \frac{\text{TORQUE (lb-in)} \times \text{rpm}}{63,025}$$

$$\text{Horsepower} = \frac{\text{TORQUE (lb-ft)} \times \text{rpm}}{5,252}$$

HORSEPOWER TO TORQUE CONVERSION TABLE

Torque lb-in @ 1 hp

rpm	LB-IN	rpm	LB-IN	rpm	LB-IN	rpm	LB-IN
3450	18	580	109	68	927	7.5	8,403
3000	21	520	121	56	1,125	6	10,504
2500	25	420	150	45	1,401	4.7	13,410
2000	32	350	180	37	1,703	4	15,756
1750	36	280	225	30	2,101	3.2	19,695
1430	44	230	274	25	2,521	2.7	23,343
1170	54	190	332	20	3,151	2.2	28,648
950	66	155	407	16.5	3,820	1.8	35,014
870	72	125	504	13.5	4,669	1.5	42,017
780	81	100	630	11	5,730	1.2	52,521
640	98	84	750	9	7,003	1	63,025

To compute torque at any horsepower, multiply torque values above by horsepower required.

Example:

10 hp @ 580 rpm, torque = 10 x 109, or 1,090 lb-ins
 1/2 hp @ 100 rpm, torque = 1/2 x 630, or 315 lb-ins

For intermediate speeds, approximate the torque from table, or apply standard torque formula above.

Electrical Formulas

Drive System Electrical Formulas

ELECTRICAL	NEED TO FIND	FORMULA
	HORSEPOWER – DC	$\frac{\text{VOLTS} \times \text{AMPS} \times \text{EFFICIENCY}}{746}$
	HORSEPOWER – AC	$\frac{\text{VOLTS} \times \text{AMPS} \times 1.732 \times \text{EFF} \times \text{PF}}{746}$
	WATTS-DC	VOLTS X AMPS
	WATTS-AC	VOLTS X AMPS X PF X 1.732
	KILOWATTS	$\frac{\text{VOLTS} \times \text{AMPS} \times \text{PF} \times 1.732}{1000}$
	AMPERES (DC)	$\frac{\text{WATTS}}{\text{VOLTS}}$
	AMPERES (AC)	$\frac{746 \times \text{HORSEPOWER}}{\text{VOLTS} \times \text{EFF} \times \text{PF} \times 1.732}$
	KVA	$\frac{\text{VOLTS} \times \text{AMPS} \times 1.732}{1000}$
	PUMP MOTOR HP	$\frac{\text{GPM} \times \text{HEAD IN FEET} \times \text{SPEC GRAVITY}}{3960 \times \text{EFFICIENCY OF PUMP}}$
FAN MOTOR HP	$\frac{\text{CFM} \times \text{PRESSURE (LB/SQ FT)}}{33000 \times \text{EFFICIENCY}}$	

To Find	Alternating Current		
	Single-Phase	Three-Phase	Direct Current
Amperes when horsepower is known	$\frac{\text{hp} \times 746}{\text{E} \times \text{Eff} \times \text{pf}}$	$\frac{\text{hp} \times 746}{1.73 \times \text{E} \times \text{Eff} \times \text{pf}}$	$\frac{\text{hp} \times 746}{\text{E} \times \text{Eff}}$
Amperes when kilowatts are known	$\frac{\text{Kw} \times 1000}{\text{E} \times \text{pf}}$	$\frac{\text{Kw} \times 1000}{1.73 \times \text{E} \times \text{pf}}$	$\frac{\text{Kw} \times 1000}{\text{E}}$
Amperes when Kva are known	$\frac{\text{Kva} \times 1000}{\text{E}}$	$\frac{\text{Kva} \times 1000}{1.73 \times \text{E}}$	-
Kilowatts	$\frac{\text{I} \times \text{E} \times \text{pf}}{1000}$	$\frac{1.73 \times \text{I} \times \text{E} \times \text{pf}}{1000}$	$\frac{\text{I} \times \text{E}}{1000}$
Kva	$\frac{\text{I} \times \text{E}}{1000}$	$\frac{1.73 \times \text{I} \times \text{E}}{1000}$	-
Horsepower = (Output)	$\frac{\text{I} \times \text{E} \times \text{Eff} \times \text{pf}}{746}$	$\frac{1.73 \times \text{I} \times \text{E} \times \text{Eff} \times \text{pf}}{746}$	$\frac{\text{I} \times \text{E} \times \text{Eff}}{746}$

I = Amperes; E = Volts; Eff = Efficiency; pf = power factor;
Kva = Kilovolt Amperes; Kw = Kilowatts; R = Ohms.

To Find	Alternating or Direct Current
Amperes when voltage and resistance are known	$\frac{\text{E}}{\text{R}}$
Voltage when resistance and current are known	I R
Resistance when voltage and current are known	$\frac{\text{E}}{\text{I}}$

RULES OF THUMB

All Values At 100 % Load

1 hp = 746 Watts or (.746 Kilowatts)

At 3,600 rpm, a motor develops 18 lb.-in. per hp
At 1,800 rpm, a motor develops 36 lb.-in. per hp
At 1,200 rpm, a motor develops 54 lb.-in. per hp

At 575 volts, a 3-phase motor draws 1 amp per hp
At 460 volts, a 3-phase motor draws 1.25 amp per hp
At 230 volts, a 3-phase motor draws 2.5 amp per hp
At 230 volts, a single-phase motor draws 5 amp per hp
At 115 volts, a single-phase motor draws 10 amp per hp

